

- | | |
|--------------------------------|----------------------------------|
| Front side | Left and right side |
| 1) LEDs show hours | 7) SET button |
| 2) LEDs show AM or PM | 8) MODE button |
| 3) Date LED | 9) Charging OFF slide |
| 4) LEDs show 10-minutes | 10) Charging ON slide |
| 5) LEDs show single minutes | 11) Micro USB charging in port |
| 6) Charging indicator (by USB) | 12) Micro USB charging out cable |

The POWERbankWatch is a binary LED watch and 500 mAh powerbank for charging mobile phones integrated in a stylish design. Now you always carry extra energy with you in case your mobile phone runs out of power. This allows you to make your phone call, check your e-mail, reply on social media etc.

The PowerbankWatch has an integrated micro USB charging cable and can juice up an average mobile phone (1.500 mAh battery) by about 25%. For iPhone 4 and 5 an adapter tip is included.

How to set time and date
Press the MODE button (8) and when LEDs illuminate, press the SET button (7) till the LEDs left under hours are flashing.

- 1) Push the MODE button (8) till the right hours and right AM or PM is selected according to the actual time. Now push the SET button (7) again.
- 2) Push the MODE button (8) till the right 10-minutes time is selected according to the actual time. Now push the SET button (7) again.
- 3) Push the MODE button (8) till the right single minutes time is selected according to the actual time. Now push the SET button (7) again.
- 4) Push the MODE button (8) till the right month number is selected according to the actual date. Now push the SET button (7) again.

5) Push the MODE button (8) till the right date in tenth of days (no LED, 10, 20 or 30) is selected according to the actual date. Now push the SET button (7) again.

6) Push the MODE button (8) till the right single day LED is selected according to the actual date. Press the SET button (7) again and you set the time and date on your powerbank watch.

How to display time and date
Press the MODE button (8) and the LEDs will show the time by illuminated LEDs in hours (left), minutes (right) and AM or PM (left below). If you press again the MODE button (8), the LEDs will show the date by number of the month (left) and day/month (right). The Date LED (3) will illuminate.

How to charge the PowerbankWatch
The internal battery of the PowerbankWatch should be charged by the included USB cable. Plug the micro USB of the charging cable into the micro USB port (11) and connect to a USB port of your computer or USB charger (not included) to charge the internal battery. During charging the indicator LED (6) will illuminate. The integrated solar cell is capable to keep your battery fully loaded during time. The integrated solar cell cannot charge the PowerbankWatch battery from empty to full.

The solar charging therefore is only for maintaining the battery capacity after fully charged by USB.



How to charge a mobile phone
Take the integrated micro USB charging cable (12) carefully out of the watch and connect to your mobile phone. Now slide the ON/OFF slide button into the ON position. Now your mobile phone is charging. After charging, please slide the ON/OFF slide button into the OFF position.

For charging iPhone 4 & 5, please use the included micro USB to iPhone 4 & 5 adapter tips.

IMPORTANT

- This product is not waterproof. Avoid high humidity
- Phones with large capacity battery / phablets can not be charged because of limited capacity of battery
- Charge your powerbank at least every 3 months by USB to guarantee full battery. Light conditions may be too low to maintain the battery by solar power (i.e. in winter time).
- After lifetime of the product, deliver the watch to local recycling point for recycling.

Technical details:
USB output 5V
Max. load current output 500 mA
Micro USB input voltage 5V
Battery Lithium, 3.7V 500 mAh
Overcharge protection: auto cut off when battery is full



- | | |
|------------------------------|---------------------------------|
| Front side | Links und rechte Seite |
| 1) LEDs zeigen Stunden | 7) Set Taste |
| 2) LEDs zeigen AM oder PM | 8) Mode Taste |
| 3) Datums LED | 9) Ladeschalter „Aus“ |
| 4) LEDs zeigen 10 Minuten | 10) Ladeschalter „Ein“ |
| 5) LEDs zeigen Einzelminuten | 11) Micro USB Ladeschacht „IN“ |
| 6) Lade Indikator (über USB) | 12) Micro USB Ladeschacht „OUT“ |

Die POWERplus PowerbankWatch ist eine LED Uhr mit integrierter 500mAh Powerbank zur Ladung von Smartphones im stylischen Design.

Nun haben Sie immer Extra - Energie dabei und verpassen keinen Anruf mehr.

Die PowerbankWatch verfügt über ein integriertes Micro USB Ladekabel und versorgt durchschnittliche Smartphones mit ca. 25% Zusatzenergie. Für das iPhone 4 u. 5 sind Adapter beigefügt.

So stellen Sie Uhrzeit und Datum ein
Drücken Sie die MODE-Taste (8) bis die LEDs leuchten, drücken Sie die SET-Taste (7), bis die LEDs links unter Stunden blinken.

- 1) Drücken Sie die MODE-Taste (8), bis die richtige Stunde gewählt ist und rechts AM oder PM. Drücken Sie nun die SET-Taste (7) wieder.
- 2) Drücken Sie die MODE-Taste (8), um die 10-Minuten Anzeige einzustellen.
- 3) Drücken Sie die MODE-Taste (8), um die Einzelminuten einzustellen. Drücken Sie nun die SET-Taste (7) wieder.
- 4) Drücken Sie die MODE-Taste (8) bis zum entsprechenden Monat. Drücken Sie nun die SET-Taste (7) wieder.

5) Drücken Sie die MODE-Taste (8) bis zum rechten Zeitpunkt in zehntel Tage (keine LED, 10, 20 oder 30) ausgewählt ist, entsprechend dem aktuellen Datum. Drücken Sie nun die SET-Taste (7) wieder.

6) Drücken Sie die MODE-Taste (8) bis die richtige Tag LED wird entsprechend dem aktuellen Datum ausgewählt. Drücken Sie die SET-Taste (7) wieder und Sie setzen die Uhrzeit und Datum auf Ihrer Powerbank Uhr.

Wie wird Zeit und Datum angezeigt?
Drücken Sie die Mode Taste (8) und die LEDs zeigen die Uhrzeit durch beleuchtete LEDs. Links werden Stunden, rechts Minuten und links unten AM oder PM angezeigt. Ein erneutes drücken der Mode Taste (8) zeigt den Monat (links) und den Tag (rechts).



Wie laden Sie die PowerbankWatch auf?
Zur Ladung der PowerbankWatch nutzen Sie das im Lieferumfang befindliche Micro USB Kabel. Das eine Ende führen Sie in den Micro USB Ladeschacht, das andere Ende in Ihren PC / Computer oder ein USB Ladegerät (befindet sich nicht im Lieferumfang). Während des Ladeprozesses leuchtet die LED Anzeige (6) auf. Die integrierte Solarzelle dient zur Batterieerhaltungsladung und kann die interne Batterie nicht aufladen.

*Stoppt die natürliche Entladung der Batterie

Wie laden Sie Ihr Smartphone auf?
Nehmen Sie das integrierte Micro USB Ladekabel (12) vorsichtig aus der Uhr und stellen Sie eine Verbindung zu Ihrem Smartphone her und stellen Sie den Ladeschalter (10) auf an. Nach der Ladung stellen Sie den Ladeschalter (10) wieder auf aus. Zur Ladung eines iPhones 4 oder 5 verwenden Sie die im Lieferumfang befindlichen Adapter.

Hinweis
Dieses Produkt ist nicht wasserdicht. Vermeiden Sie hohe Luftfeuchtigkeit. Akkus von Smartphones/Phablets mit großer Kapazität können nicht geladen werden. Laden Sie die Powerbank mindestens alle 3 Monate auf. Aufgrund zu geringer Einstrahlung kann die Solarzelle (z.B. im Winter) nicht optimal arbeiten.

Technical details:
USB Ausgang 5V
Max. Ladestrom Ausgang 500mAh
Micro USB Eingangsspannung 5V
Lithium Batterie 3.7V / 500mAh
Überladeschutz durch Verwendung neuester Chip Technologie



- | | |
|------------------------------|---------------------------------|
| Front side | Links und rechte Seite |
| 1) LEDs zeigen Stunden | 7) Set Taste |
| 2) LEDs zeigen AM oder PM | 8) Mode Taste |
| 3) Datums LED | 9) Ladeschalter „Aus“ |
| 4) LEDs zeigen 10 Minuten | 10) Ladeschalter „Ein“ |
| 5) LEDs zeigen Einzelminuten | 11) Micro USB Ladeschacht „IN“ |
| 6) Lade Indikator (über USB) | 12) Micro USB Ladeschacht „OUT“ |

Die POWERplus PowerbankWatch ist eine binary LED watch and 500 mAh powerbank for charging mobile phones integrated in a stylish design. Now you always carry extra energy with you in case your mobile phone runs out of power. This allows you to make your phone call, check your e-mail, reply on social media etc.

The PowerbankWatch has an integrated micro USB charging cable and can juice up an average mobile phone (1.500 mAh battery) by about 25%. For iPhone 4 and 5 an adapter tip is included.

How to set time and date
Press the MODE button (8) and when LEDs illuminate, press the SET button (7) till the LEDs left under hours are flashing.

- 1) Push the MODE button (8) till the right hours and right AM or PM is selected according to the actual time. Now push the SET button (7) again.
- 2) Push the MODE button (8) till the right 10-minutes time is selected according to the actual time. Now push the SET button (7) again.
- 3) Push the MODE button (8) till the right single minutes time is selected according to the actual time. Now push the SET button (7) again.
- 4) Push the MODE button (8) till the right month number is selected according to the actual date. Now push the SET button (7) again.

5) Push the MODE button (8) till the right date in tenth of days (no LED, 10, 20 or 30) is selected according to the actual date. Now push the SET button (7) again.

6) Push the MODE button (8) till the right single day LED is selected according to the actual date. Press the SET button (7) again and you set the time and date on your powerbank watch.

How to display time and date
Press the MODE button (8) and the LEDs will show the time by illuminated LEDs in hours (left), minutes (right) and AM or PM (left below). If you press again the MODE button (8), the LEDs will show the date by number of the month (left) and day/month (right). The Date LED (3) will illuminate.

How to charge the PowerbankWatch
The internal battery of the PowerbankWatch should be charged by the included USB cable. Plug the micro USB of the charging cable into the micro USB port (11) and connect to a USB port of your computer or USB charger (not included) to charge the internal battery. During charging the indicator LED (6) will illuminate. The integrated solar cell is capable to keep your battery fully loaded during time. The integrated solar cell cannot charge the PowerbankWatch battery from empty to full.

The solar charging therefore is only for maintaining the battery capacity after fully charged by USB.



How to charge a mobile phone
Take the integrated micro USB charging cable (12) carefully out of the watch and connect to your mobile phone. Now slide the ON/OFF slide button into the ON position. Now your mobile phone is charging. After charging, please slide the ON/OFF slide button into the OFF position.

For charging iPhone 4 & 5, please use the included micro USB to iPhone 4 & 5 adapter tips.

IMPORTANT

- This product is not waterproof. Avoid high humidity
- Phones with large capacity battery / phablets can not be charged because of limited capacity of battery
- Charge your powerbank at least every 3 months by USB to guarantee full battery. Light conditions may be too low to maintain the battery by solar power (i.e. in winter time).
- After lifetime of the product, deliver the watch to local recycling point for recycling.

Technical details:
USB output 5V
Max. load current output 500 mA
Micro USB input voltage 5V
Battery Lithium, 3.7V 500 mAh
Overcharge protection: auto cut off when battery is full



- | | |
|------------------------------|---------------------------------|
| Front side | Links und rechte Seite |
| 1) LEDs zeigen Stunden | 7) Set Taste |
| 2) LEDs zeigen AM oder PM | 8) Mode Taste |
| 3) Datums LED | 9) Ladeschalter „Aus“ |
| 4) LEDs zeigen 10 Minuten | 10) Ladeschalter „Ein“ |
| 5) LEDs zeigen Einzelminuten | 11) Micro USB Ladeschacht „IN“ |
| 6) Lade Indikator (über USB) | 12) Micro USB Ladeschacht „OUT“ |

Die POWERplus PowerbankWatch ist eine LED Uhr mit integrierter 500mAh Powerbank zur Ladung von Smartphones im stylischen Design.

Nun haben Sie immer Extra - Energie dabei und verpassen keinen Anruf mehr.

Die PowerbankWatch verfügt über ein integriertes Micro USB Ladekabel und versorgt durchschnittliche Smartphones mit ca. 25% Zusatzenergie. Für das iPhone 4 u. 5 sind Adapter beigefügt.

So stellen Sie Uhrzeit und Datum ein
Drücken Sie die MODE-Taste (8) bis die LEDs leuchten, drücken Sie die SET-Taste (7), bis die LEDs links unter Stunden blinken.

- 1) Drücken Sie die MODE-Taste (8), bis die richtige Stunde gewählt ist und rechts AM oder PM. Drücken Sie nun die SET-Taste (7) wieder.
- 2) Drücken Sie die MODE-Taste (8), um die 10-Minuten Anzeige einzustellen.
- 3) Drücken Sie die MODE-Taste (8), um die Einzelminuten einzustellen. Drücken Sie nun die SET-Taste (7) wieder.
- 4) Drücken Sie die MODE-Taste (8) bis zum entsprechenden Monat. Drücken Sie nun die SET-Taste (7) wieder.

5) Drücken Sie die MODE-Taste (8) bis zum rechten Zeitpunkt in zehntel Tage (keine LED, 10, 20 oder 30) ausgewählt ist, entsprechend dem aktuellen Datum. Drücken Sie nun die SET-Taste (7) wieder.

6) Drücken Sie die MODE-Taste (8) bis die richtige Tag LED wird entsprechend dem aktuellen Datum ausgewählt. Drücken Sie die SET-Taste (7) wieder und Sie setzen die Uhrzeit und Datum auf Ihrer Powerbank Uhr.

Wie wird Zeit und Datum angezeigt?
Drücken Sie die Mode Taste (8) und die LEDs zeigen die Uhrzeit durch beleuchtete LEDs. Links werden Stunden, rechts Minuten und links unten AM oder PM angezeigt. Ein erneutes drücken der Mode Taste (8) zeigt den Monat (links) und den Tag (rechts).



Wie laden Sie die PowerbankWatch auf?
Zur Ladung der PowerbankWatch nutzen Sie das im Lieferumfang befindliche Micro USB Kabel. Das eine Ende führen Sie in den Micro USB Ladeschacht, das andere Ende in Ihren PC / Computer oder ein USB Ladegerät (befindet sich nicht im Lieferumfang). Während des Ladeprozesses leuchtet die LED Anzeige (6) auf. Die integrierte Solarzelle dient zur Batterieerhaltungsladung und kann die interne Batterie nicht aufladen.

*Stoppt die natürliche Entladung der Batterie

Wie laden Sie Ihr Smartphone auf?
Nehmen Sie das integrierte Micro USB Ladekabel (12) vorsichtig aus der Uhr und stellen Sie eine Verbindung zu Ihrem Smartphone her und stellen Sie den Ladeschalter (10) auf an. Nach der Ladung stellen Sie den Ladeschalter (10) wieder auf aus. Zur Ladung eines iPhones 4 oder 5 verwenden Sie die im Lieferumfang befindlichen Adapter.

Hinweis
Dieses Produkt ist nicht wasserdicht. Vermeiden Sie hohe Luftfeuchtigkeit. Akkus von Smartphones/Phablets mit großer Kapazität können nicht geladen werden. Laden Sie die Powerbank mindestens alle 3 Monate auf. Aufgrund zu geringer Einstrahlung kann die Solarzelle (z.B. im Winter) nicht optimal arbeiten.

Technical details:
USB Ausgang 5V
Max. Ladestrom Ausgang 500mAh
Micro USB Eingangsspannung 5V
Lithium Batterie 3.7V / 500mAh
Überladeschutz durch Verwendung neuester Chip Technologie



- | | |
|--------------------------------|----------------------------------|
| Front side | Links und rechte Seite |
| 1) LEDs show hours | 7) SET button |
| 2) LEDs show AM or PM | 8) MODE button |
| 3) Date LED | 9) Charging OFF slide |
| 4) LEDs show 10-minutes | 10) Charging ON slide |
| 5) LEDs show single minutes | 11) Micro USB charging in port |
| 6) Charging indicator (by USB) | 12) Micro USB charging out cable |

The POWERplus PowerbankWatch is a binary LED watch and 500 mAh powerbank for charging mobile phones integrated in a stylish design. Now you always carry extra energy with you in case your mobile phone runs out of power. This allows you to make your phone call, check your e-mail, reply on social media etc.

The PowerbankWatch has an integrated micro USB charging cable and can juice up an average mobile phone (1.500 mAh battery) by about 25%. For iPhone 4 and 5 an adapter tip is included.

How to set time and date
Press the MODE button (8) and when LEDs illuminate, press the SET button (7) till the LEDs left under hours are flashing.

- 1) Push the MODE button (8) till the right hours and right AM or PM is selected according to the actual time. Now push the SET button (7) again.
- 2) Push the MODE button (8) till the right 10-minutes time is selected according to the actual time. Now push the SET button (7) again.
- 3) Push the MODE button (8) till the right single minutes time is selected according to the actual time. Now push the SET button (7) again.
- 4) Push the MODE button (8) till the right month number is selected according to the actual date. Now push the SET button (7) again.

5) Push the MODE button (8) till the right date in tenth of days (no LED, 10, 20 or 30) is selected according to the actual date. Now push the SET button (7) again.

6) Push the MODE button (8) till the right single day LED is selected according to the actual date. Press the SET button (7) again and you set the time and date on your powerbank watch.

How to display time and date
Press the MODE button (8) and the LEDs will show the time by illuminated LEDs in hours (left), minutes (right) and AM or PM (left below). If you press again the MODE button (8), the LEDs will show the date by number of the month (left) and day/month (right). The Date LED (3) will illuminate.

How to charge the PowerbankWatch
The internal battery of the PowerbankWatch should be charged by the included USB cable. Plug the micro USB of the charging cable into the micro USB port (11) and connect to a USB port of your computer or USB charger (not included) to charge the internal battery. During charging the indicator LED (6) will illuminate. The integrated solar cell is capable to keep your battery fully loaded during time. The integrated solar cell cannot charge the PowerbankWatch battery from empty to full.

The solar charging therefore is only for maintaining the battery capacity after fully charged by USB.


How to charge a mobile phone
Take the integrated micro USB charging cable (12) carefully out of the watch and connect to your mobile phone. Now slide the ON/OFF slide button into the ON position. Now your mobile phone is charging. After charging, please slide the ON/OFF slide button into the OFF position.

For charging iPhone 4 & 5, please use the included micro USB to iPhone 4 & 5 adapter tips.

IMPORTANT

- This product is not waterproof. Avoid high humidity
- Phones with large capacity battery / phablets can not be charged because of limited capacity of battery
- Charge your powerbank at least every 3 months by USB to guarantee full battery. Light conditions may be too low to maintain the battery by solar power (i.e. in winter time).
- After lifetime of the product, deliver the watch to local recycling point for recycling.

Technical details:
USB output 5V
Max. load current output 500 mA
Micro USB input voltage 5V
Battery Lithium, 3.7V 500 mAh
Overcharge protection: auto cut off when battery is full



- | | |
|------------------------------|---------------------------------|
| Front side | Links und rechte Seite |
| 1) LEDs zeigen Stunden | 7) Set Taste |
| 2) LEDs zeigen AM oder PM | 8) Mode Taste |
| 3) Datums LED | 9) Ladeschalter „Aus“ |
| 4) LEDs zeigen 10 Minuten | 10) Ladeschalter „Ein“ |
| 5) LEDs zeigen Einzelminuten | 11) Micro USB Ladeschacht „IN“ |
| 6) Lade Indikator (über USB) | 12) Micro USB Ladeschacht „OUT“ |

Die POWERplus PowerbankWatch ist eine LED Uhr mit integrierter 500mAh Powerbank zur Ladung von Smartphones im stylischen Design.

Nun haben Sie immer Extra - Energie dabei und verpassen keinen Anruf mehr.

Die PowerbankWatch verfügt über ein integriertes Micro USB Ladekabel und versorgt durchschnittliche Smartphones mit ca. 25% Zusatzenergie. Für das iPhone 4 u. 5 sind Adapter beigefügt.

So stellen Sie Uhrzeit und Datum ein
Drücken Sie die MODE-Taste (8) bis die LEDs leuchten, drücken Sie die SET-Taste (7), bis die LEDs links unter Stunden blinken.

- 1) Drücken Sie die MODE-Taste (8), bis die richtige Stunde gewählt ist und rechts AM oder PM. Drücken Sie nun die SET-Taste (7) wieder.
- 2) Drücken Sie die MODE-Taste (8), um die 10-Minuten Anzeige einzustellen.
- 3) Drücken Sie die MODE-Taste (8), um die Einzelminuten einzustellen. Drücken Sie nun die SET-Taste (7) wieder.
- 4) Drücken Sie die MODE-Taste (8) bis zum entsprechenden Monat. Drücken Sie nun die SET-Taste (7) wieder.

5) Drücken Sie die MODE-Taste (8) bis zum rechten Zeitpunkt in zehntel Tage (keine LED, 10, 20 oder 30) ausgewählt ist, entsprechend dem aktuellen Datum. Drücken Sie nun die SET-Taste (7) wieder.

6) Drücken Sie die MODE-Taste (8) bis die richtige Tag LED wird entsprechend dem aktuellen Datum ausgewählt. Drücken Sie die SET-Taste (7) wieder und Sie setzen die Uhrzeit und Datum auf Ihrer Powerbank Uhr.

Wie wird Zeit und Datum angezeigt?
Drücken Sie die Mode Taste (8) und die LEDs zeigen die Uhrzeit durch beleuchtete LEDs. Links werden Stunden, rechts Minuten und links unten AM oder PM angezeigt. Ein erneutes drücken der Mode Taste (8) zeigt den Monat (links) und den Tag (rechts).

Wie laden Sie die PowerbankWatch auf?
Zur Ladung der PowerbankWatch nutzen Sie das im Lieferumfang befindliche Micro USB Kabel. Das eine Ende führen Sie in den Micro USB Ladeschacht, das andere Ende in Ihren PC / Computer oder ein USB Ladegerät (befindet sich nicht im Lieferumfang). Während des Ladeprozesses leuchtet die LED Anzeige (6) auf. Die integrierte Solarzelle dient zur Batterieerhaltungsladung und kann die interne Batterie nicht aufladen.

*Stoppt die natürliche Entladung der Batterie

Wie laden Sie Ihr Smartphone auf?
Nehmen Sie das integrierte Micro USB Ladekabel (12) vorsichtig aus der Uhr und stellen Sie eine Verbindung zu Ihrem Smartphone her und stellen Sie den Ladeschalter (10) auf an. Nach der Ladung stellen Sie den Ladeschalter (10) wieder auf aus. Zur Ladung eines iPhones 4 oder 5 verwenden Sie die im Lieferumfang befindlichen Adapter.

Hinweis
Dieses Produkt ist nicht wasserdicht. Vermeiden Sie hohe Luftfeuchtigkeit. Akkus von Smartphones/Phablets mit großer Kapazität können nicht geladen werden. Laden Sie die Powerbank mindestens alle 3 Monate auf. Aufgrund zu geringer Einstrahlung kann die Solarzelle (z.B. im Winter) nicht optimal arbeiten.

Technical details:
USB Ausgang 5V
Max. Ladestrom Ausgang 500mAh
Micro USB Eingangsspannung 5V
Lithium Batterie 3.7V / 500mAh
Überladeschutz durch Verwendung neuester Chip Technologie

